Current R15 - 11 DMX Personalities

Personality Number	Personality Description	Slot Count	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	37	37	38
1	Local	0																																						
2	R15 Basic 8-bit	3	DIM	CCT	ANGLE																																			
3	R15 Basic 16-bit	6	DIM		CCT		ANGLE																																	
4	R15 Beam 8-bit	11	Master DIM	CCT	Zone 1 DIM	Zone 2 DIM	Zone 3 DIM	Zone 4 DIM	Zone 5 DIM	Zone 6 DIM	Zone 7 DIM	Zone 8 DIM	Zone 9 DIM																											
5	R15 Beam 16-bit	22	Master DIM		CCT		Zone 1 DIM		Zone 2 DIM		Zone 3 DIM		Zone 4 DIM		Zone 5 DIM		Zone 6 DIM		Zone 7 DIM		Zone 8 DIM		Zone 9 DIM																	
6	R15 Beam K 8-bit	19	Master DIM	Zone 1 DIM	Zone 1 CCT	Zone 2 dim	Zone 2 CCT	Zone 3 dim	Zone 3 CCT	Zone 4 DIM	Zone 4 CCT	Zone 5 DIM	Zone 5 CCT	Zone 6 DIM	Zone 6 CCT	Zone 7 DIM	Zone 7 CCT	Zone 8 DIM	Zone 8 CCT	Zone 9 DIM	Zone 9 CCT																			
7	R15 Beam K 16-bit	38	Master DIM		Zone 1 DIM		Zone 1 CCT		Zone 2 DIM		Zone 2 CCT		Zone 3 DIM		Zone 3 CCT		Zone 4 DIM		Zone 4 CCT		Zone 5 DIM		Zone 5 CCT		Zone 6 DIM		Zone 6 CCT		Zone 7 DIM		Zone 7 CCT		Zone 8 DIM		Zone 8 CCT		Zone 9 DIM		Zone 9 CCT	
8	DIM Only 8-bit	1	Master DIM																																					
9	DIM Only 16-bit	2	Master DIM																																					
10	DIM + CCT 8-bit	2	Master DIM	Master CCT																																				
11	DIM + CCT 16-bit	4	Master DIM		Master CCT																																			